



Technische Änderungen vorbehalten, alle Angaben ohne Gewähr / Subject to technical modifications; no responsibility is accepted for the accuracy of this information. © EUCHNER GmbH + Co. KG · Maße in mm / Dimensions in mm

**A1:**  
Handrad 100 Impulse  
handwheel 100 pulses  
RS422 / A05




X1/6	0 V	WH	ws	A
X1/5	UB: +5 V +/-5%	BN	br	B
X1/1	A	GN	gn	C
X1/2	/A	YE	ge	D
X1/3	B	GY	gr	E
X1/4	/B	PK	rs	F


**S1:**  
NOT-AUS  
emergency-stop



		BU	bl	G
		RD	rt	H
		BK	sw	J
		VT	vt	K




**S7:**  
ZXE  
Zustimmtaster links  
enabling push button  
left



X2/3		RDBU	rtbl	M
X2/2		GNWH	wsgn	N
X2/4		BNGN	brgn	P
X2/1		YEWB	wsgb	R


**S4:**  
Taste links  
push button left  
**S5:**  
Taste mitte  
push button middle  
**S6:**  
Taste rechts  
push button right



X3:2		BNYE	gebr	S
X3:3		GYWH	wsgR	T
X3:4		BNRD	brRt	a
X3:1				

S2	DCBA	
1	0000	X
2	0001	Y
3	0011	Z
4	0010	4
5	0110	5
6	0111	6


**S2:**  
**Achswahl**  
Stufenschalter links  
selector switch left  
6-stellig  
6 positions



LP2		BNGY	grbr	U
LP1		WHPK	wrsr	V
LP3		BNPK	rsbr	W
LP5				
LP6				

S3	DCBA	
1	0000	0
2	0001	1
3	0011	10
4	0010	100
5	0110	1000

**S3:**  
**Inkrementauswahl**  
Stufenschalter rechts  
selector switch right  
5-stellig  
5 positions



LP2		BUWH	wsbl	X
LP1		BNBU	brbl	Y
LP3		RDWH	wstr	Z
LP5				
LP6				

Litzen nicht angeschlossen  
wires not connected

		GYPK	grrs	L
		BKWH	wssw	b
		BKBN	brsw	c
		GNGY	grgn	d
		YEGY	gegr	e
		shield	Schirm	

Steckverbinder:  
Burndy, Metall, 28 polig  
connector:  
Burndy, metal, 28 pin

Leitung / cable:  
28x0,14²