



- X1** 7/8" Power (Stecker/ male) 4-polig  
**X2** 7/8" Power (Buchse/ female) 4-polig  
**X3 / X4** M12 D-coded (Buchse/ female) 4-polig

**X6** (Signal stack modul)  
 M12 5-polig (Buchse) - nicht ausgerichtet  
 M12 5-pin (female) - not aligned



...-L-...



**Inklusive:**  
 3 Stück Einlegeschilder  
 silberfarben, selbstklebend.  
 Ohne Aufschrift (12,5x27mm)

**Including:**  
 3 pcs. insertion plates, silver,  
 self-adhesive.  
 Without inscription (12,5x27mm)

Blenden-Set für Taster inklusive:

**Lens-Set** for push-buttons included:

- 2x weiss / white  
 1x blau / blue  
 1x gelb / yellow  
 1x grün / green  
 1x rot / red

Blenden-Set für Taster inklusive:

**Lens-Set** for push-buttons included:

- 1x weiss / white  
 1x weiss / white  
 1x grün / green  
 1x weiss / white  
 1x weiss / white  
 1x weiss / white

### Betriebsanleitung beachten

(bei Abweichungen zwischen Datenblatt u. Betriebsanleitung gelten die Daten des Datenblattes)

### Please observe the operating instructions

(in case of disagreement between data sheet and operating instructions, the information of the data sheet are to be considered)

	MGB-H	MGB-L...	MGB-E..	Türanschlag Door hinge	S1 NOT-HALT Taster beleuchtet Emergency stop illuminated	S90 Taster beleuchtet Push-button illuminated	S91 Taster beleuchtet Push-button illuminated	S92 Taster beleuchtet Push-button illuminated
MGB-L1B-EIC-R-136492		X		R				
<b>MGB-L1HB-EIC-R-160892</b>	X	X			X	X	X	X
MGB-L1B-EIC-L-136500		X		L				
<b>MGB-L1HB-EIC-L-160893</b>	X	X						

### EtherNet / IP

Datenbytes / Data bytes  
Datenblöcke / Data blocks

Eingangsbereich / Input range:

	Bit	7	6	5	4	3	2	1	0
Standardfunktionen Standard functions	Connection header	Byte 0	-	-	-	-	DA	CF	RM
	Connection header	Byte 1	DiagnosticSequenceCount						
	Connection header	Byte 2	-	-	-	-	-	-	-
	Connection header	Byte 3	-	-	-	-	-	-	-
	Connection header	Byte 4	-	-	-	-	-	-	FI.ES
Sichere Funktionen Safe functions (FI.)	Failsafe input 0	Byte 5	FI.UK	FI.SK	-	-	FI.L	FI.B	FI.D
	Failsafe input 1	Byte 6	-	-	-	S92.1	-	S91.1	-
	Input 0	Byte 7	-	-	-	-	-	-	-
	Input 1	Byte 8	-	-	-	-	-	-	-
	Input 2	Byte 9	-	-	-	-	-	-	-
Standardfunktionen Standard functions	Diagnostics	Byte 10	D.LT	-	D.OL	-	D.ES	D.PF	-
	Fault code	Byte 11	FaultCode						
	Fault code	Byte 11	FaultCode						

Ausgangsbereich / Output range:

	Bit	7	6	5	4	3	2	1	0
Sichere Funktion Safe function (FO.)	Failsafe output 0	Byte 0	-	-	-	-	-	-	FO.L
	Output 0	Byte 1	-	-	-	-	H92	H91	H90
	Output 1	Byte 2	-	-	-	-	-	-	H1
Standardfunktionen Standard functions	Control and ACK	Byte 3	Q.PF	Q.G	-	-	X6.5	X6.4	X6.2

DA = Diagnostic active  
 CF = Connection faulted  
 RM = Run mode  
 FI.UK = D and B and L

FI.SK = D and B  
 FI.L = Guard locking  
 FI.B = Bolt position  
 FI.D = Door position

D.LT = Lifetime  
 D.OL = Guard locking  
 D.ES = Emergency stop  
 D.PF = Plausibility fault

FO.L = Guard locking  
 Q.PF = Acknowledge plausibility fault  
 Q.G = Acknowledge all